

T6M27S

T6M27S CMOS 1 CHIP LSI FOR LCD ELECTRONIC CALCULATOR

The T6M27S is a 1 chip microcomputer for 8-digits + 1-digit electronic scientific calculation.

T6M27S is the complete single chip CMOS LSI for electronic calculator with 8 digit, 27 function, and fractional number calculation with the following features.

FEATURES

- Display 8 display digits plus 1 digits code at the right margin.

- Scientific display.

Mantissa 6 digits plus exponent 2 digits plus negative code 2 digits.

- Fractional number display.

9 digits plus negative code 1 digit.


- Other than above

Mantissa 8 digits plus negative code 1 digit.

- 9 kinds of special display

M	Memory	DEG	Degree
-	Minus	RAD	Radian
E	Error	GRAD	Gradian
INV	Inverse	()	Parenthesis calculation

- The minus sign of the mantissa is floating minus.
- The arithmetic key operation in clouding Y^x has same sequence as mathematical equation. 4 pending operations are allowed and () are up to continuous 15 levels.
- Fractional number calculation.
- One independent accumulating memory.
- Direct drive for FEM LCD (1/3 prebias, 1/4 duty) .
- Automatic power on clear.
- Low power consumption. $V_{SS} = -3.0V$ single power supply.
- The 60 pin flat package is used.




LQFP60-P-1414-0.80

Weight : 0.66g (Typ.)

980910EBA2

● TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.

SYSTEM BLOCK DIAGRAM




(Note) Input capacity ≤ 300 (pF) at $V_{DD} = -2.6$ (V)
 Key resistance ≤ 1.5 (k Ω) at $V_{DD} = -2.6$ (V)

980910EBA2'


- The products described in this document are subject to the foreign exchange and foreign trade laws.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.

CONNECTION OF LCD

SEGMENT




COMMON




SET KEY LAYOUT (Example)

INV				OFF	ON C / CE
SIN SIN ⁻¹	COS COS ⁻¹	TAN TAN ⁻¹	DRG DRG▶	π	%
\ln e ^x	\log 10 ^x	Y^x	x^2	$\sqrt{\quad}$	1 / x
RM	X→M	M +	a b / c	d / c	
7	8	9	()	
4	5	6	×	÷	
1	2	3	+	-	
0	.	+ / -	EXP	=	

KEY LAYOUT



PIN LAYOUT



OPERATION EXAMPLE

CALCULATION EXAMPLE	KEY OPERATION	DISPLAY		
		MANTISSA	SIGN	EXPONENT
Addition, Subtraction				
● 123 + 654 = 777	123 <input type="text"/> + <input type="text"/> 654 <input type="text"/> =	777		
● 19 + 19 + 19 + 19 = 76	19 <input type="text"/> + <input type="text"/> = <input type="text"/> = <input type="text"/> =	76		
● 2.34 – 3.45 = – 1.11	2.34 <input type="text"/> – <input type="text"/> 3.45 <input type="text"/> =	– 1.11		
Multiplication, Division				
● 98765 × (– 4321) = – 4.26763 × 10 ⁸	98765 <input type="text"/> × <input type="text"/> 4321 <input type="text"/> + / – <input type="text"/> =	– 4.26763		08
● (4.5 × 10 ⁶) ÷ 7.8 = 576923.08	4.5 <input type="text"/> EXP <input type="text"/> 6 <input type="text"/> ÷ <input type="text"/> 7.8 <input type="text"/> =	576923.08		
Parenthesis				
● $\frac{11 - 13}{15 + 17} = - 0.0625$	<input type="text"/> (<input type="text"/> 11 <input type="text"/> – <input type="text"/> 13 <input type="text"/>) <input type="text"/> ÷ <input type="text"/> (<input type="text"/> 15 <input type="text"/> + <input type="text"/> 17 <input type="text"/>) <input type="text"/> =	– 0.0625		
● 98 ÷ [(7 + 4) × (5 – 6)] = – 8.9090909	98 <input type="text"/> ÷ <input type="text"/> (<input type="text"/> (<input type="text"/> 7 <input type="text"/> + <input type="text"/> 4 <input type="text"/>) <input type="text"/> × <input type="text"/> (<input type="text"/> 5 <input type="text"/> – <input type="text"/> 6 <input type="text"/>) <input type="text"/> =	– 8.9090909		

CALCULATION EXAMPLE	KEY OPERATION	DISPLAY		
		MANTISSA	SIGN	EXPONENT
Constant Calculation				
● 0.12 + 0.78 = 0.9 0.34 + 0.78 = 1.12 0.56 + 0.78 = 1.34	0.12 $\boxed{+}$ 0.78 $\boxed{=}$ 0.34 $\boxed{=}$ 0.56 $\boxed{=}$	0.9 1.12 1.34		
● 987 - 100 = 887 654 - 100 = 554 321 - 100 = 221	987 $\boxed{-}$ 100 $\boxed{=}$ 654 $\boxed{=}$ 321 $\boxed{=}$	887 554 221		
● 1.1 × 4.4 = 4.84 2.2 × 4.4 = 9.68 3.3 × 4.4 = 14.52	1.1 $\boxed{\times}$ 4.4 $\boxed{=}$ 2.2 $\boxed{=}$ 3.3 $\boxed{=}$	4.84 9.68 14.52		
● 500 ÷ 4 = 125 600 ÷ 4 = 150 700 ÷ 4 = 175	500 $\boxed{\div}$ 4 $\boxed{=}$ 600 $\boxed{=}$ 700 $\boxed{=}$	125 150 175		
● 2 ⁵ = 32 3 ⁵ = 243 4 ⁵ = 1024	2 $\boxed{y^x}$ 5 $\boxed{=}$ 3 $\boxed{=}$ 4 $\boxed{=}$	32 243 1024		
● 12.3 + 4 × 5.6 = 34.7 23.4 + 4 × 5.6 = 45.8 34.5 + 4 × 5.6 = 56.9	12.3 $\boxed{+}$ 4 $\boxed{\times}$ 5.6 $\boxed{=}$ 23.4 $\boxed{=}$ 34.5 $\boxed{=}$	34.7 45.8 56.9		
Memory Calculation				
(Total calculation) 9 × 8 = 72 7 × 6 = 42 +) 5 × 4 = 20 134	$\boxed{C-CE} \boxed{X \rightarrow M} 9 \boxed{\times} 8 \boxed{=} \boxed{M+}$ 7 $\boxed{\times} 6 \boxed{=} \boxed{M+}$ 5 $\boxed{\times} 4 \boxed{=} \boxed{M+} \boxed{RM}$	72 42 20 134		
Fractional Calculation				
● $\frac{1}{2} + \frac{1}{3} + \frac{1}{4} = 1\frac{1}{12}$	1 $\boxed{ab/c} 2 \boxed{+} 1 \boxed{ab/c} 3 \boxed{+}$ 1 $\boxed{ab/c} 4 \boxed{=}$ $\boxed{d/c}$ $\boxed{ab/c}$ $\boxed{ab/c}$	$1\frac{1}{12}$ $1\frac{1}{12}$ 1.0833333 $1\frac{1}{12}$		
● $5\frac{1}{6} - 7\frac{1}{8} = -1\frac{23}{24}$	5 $\boxed{ab/c} 1 \boxed{ab/c} 6 \boxed{-} 7 \boxed{ab/c}$ 1 $\boxed{ab/c} 8 \boxed{=}$ $\boxed{d/c}$ $\boxed{ab/c}$	$-1\frac{23}{24}$ $-1\frac{23}{24}$ -47 $\frac{24}{24}$ -1.9583333		

CALCULATION EXAMPLE	KEY OPERATION	DISPLAY		
		MANTISSA	SIGN	EXPONENT
Functional Calculation				
(Trigonometry)				
• $\sin 30^\circ = 0.5$ [DEG]	<div>DRG [DEG] 30 SIN</div>	0.5	[DEG]	
• $\cos \frac{2}{3} \pi$ [RAD] = - 0.5	<div>DRG [RAD] (2 ÷ 3 × π)</div> <div>COS</div>	- 0.5	[RAD]	
• $\tan 150^\circ = - 1$ [GRAD]	<div>DRG [GRAD] 150 TAN</div>	- 1	[GRAD]	
• $1 - \cos^2 60^\circ = 0.75$ [DEG]	<div>DRG [DEG] 1 - 60 COS x² =</div>	0.75	[DEG]	
(Inverse trigonometry)				
• $\sin^{-1} 0.5 = - 30^\circ$ [DEG]	<div>DRG [DEG] 0.5 + / - SIN⁻¹</div>	- 30	[DEG]	
• $\cos^{-1} 1$ = 3.1415927 [RAD]	<div>DRG [RAD] 1 + / - COS⁻¹</div>	3.1415927	[RAD]	
• $\tan^{-1} 1 = 50^\circ$ [GRAD]	<div>DRG [GRAD] 1 TAN⁻¹</div>	50	[GRAD]	
(Exponential)				
• $e^1 = 2.7182818$	<div>1 e^x</div>	2.7182818		
• $e^{1.5} \times 10^{2.5} = 1417.2345$	<div>1.5 e^x × 2.5 10^x =</div>	1417.2345		
(Natural logarithm)				
• $\ln 30 = 3.4011974$	<div>30 LN</div>	3.4011974		
(Common logarithm)				
• $\log 100 = 2$	<div>100 LOG</div>	2		
• $\log \sqrt{3} + \log \sqrt{5}$ = 0.5880456	<div>3 √ LOG + 5 √ LOG =</div>	0.5880456		
(Square root)				
• $\sqrt{2} = 1.4142136$	<div>2 √</div>	1.4142136		
• $\sqrt{5} \times \sqrt{7} = 5.9160798$	<div>5 √ × 7 √ =</div>	5.9160798		
(Square)				
• $3^2 + 4^2 = 25$	<div>3 x² + 4 x² =</div>	25		
• $(2.34 \times 10^5)^2$ = 5.4756×10^{10}	<div>2.34 EXP 5 x²</div>	5.4756		10
(Power)				
• $2^{10} = 1024$	<div>2 y² 10 =</div>	1024		
• $3^{-19} = 8.60391 \times 10^{-10}$	<div>3 y² 19 + / - =</div>	8.60391	-	10
• $\sqrt[3]{8} (= 8^{1/3}) = 2$	<div>8 y² 3 1/x =</div>	2		
• $\sqrt[4]{81} = 3$	<div>81 √ √</div>	3		
(Reciprocal)				
• $\frac{1}{3} + \frac{1}{5} = 0.5333333$	<div>3 1/x + 5 1/x =</div>	0.5333333		
• $\frac{1}{1.23 \times 10^{17}}$ = 8.13008×10^{-18}	<div>1.23 EXP 17 1/x</div>	8.13008	-	18
Pi Calculation				
• $5 \times \pi = 15.707963$	<div>5 × π =</div>	15.707963		

CALCULATION EXAMPLE	KEY OPERATION	DISPLAY		
		MANTISSA	SIGN	EXPONENT
Percent Calculation				
<ul style="list-style-type: none">What is 15% of 400? $400 \times \frac{15}{100} = 60$	$400 \times 15 \% =$	60		
<ul style="list-style-type: none">3 equals what percent of 24? $\frac{3}{24} \times 100 = 12.5$	$3 \div 24 \% =$	12.5		
<ul style="list-style-type: none">A 25% add on to 800 $800 + 800 \times \frac{25}{100} = 1000$	$800 + 25 \% =$	1000		
<ul style="list-style-type: none">A 18% deduction on 700 $700 - 700 \times \frac{18}{100} = 574$	$700 - 18 \% =$	574		

MAXIMUM RATINGS

PARAMETER	SYMBOL	RATING	UNIT
Supply Voltage	V_{SS}	+ 0.3 ~ - 3.5	V
Input Voltage	V_{IN}	+ 0.3 ~ V_{DD} - 0.3	V
Operating Temperature	T_{opr}	0 ~ 40	°C
Storage Temperature	T_{stg}	- 55 ~ 125	°C

ELECTRICAL CHARACTERISTICS ($V_{SS} = -3.0 \pm 0.2V$, $V_{DD} = 0V$, $T_a = 25 \pm 1.5^\circ C$)


PARAMETER	SYMBOL	TEST CIRCUIT	PIN NAME	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Operating Voltage	—	—	—	—	- 2.5	- 3.0	- 3.4	V
Supply Current	I_{DD} WAIT	—	—	$V_{SS} = -3.0V$, wait	—	26	—	μA
Supply Current	I_{DD} OP	—	—	$V_{SS} = -3.0V$, operate	—	52	78	μA
Supply Current	I_{DD} OFF	—	—	$V_{SS} = -3.0V$, off	—	1	3	μA
Oscillating Frequency	f_{ϕ} WAIT	—	—	$V_{SS} = -3.0V$, wait	18	30	42	kHz
Oscillating Frequency	f_{ϕ} OP	—	—	$V_{SS} = -3.0V$, operate	42	70	98	kHz
Frame Frequency	fF	—	—	$V_{SS} = -3.0V$, wait	70	117	164	Hz
Timer	T timer	—	—	$V_{SS} = -3.0V$	428	600	1000	s
"1" Input Voltage	V_{IH}	—	$K_1 \sim K_4$	—	$V_{SS} + 0.5$	—	V_{SS}	V
"0" Input Voltage	V_{IL}	—	$K_1 \sim K_4$	—	V_{DD}	—	- 0.5	V
"1" Output Resistance	R_{KEY}	—	SEG	$V_{OUT} = V_{SS} + 0.5V$: KEY STROBE	—	—	2	$k\Omega$
"0" Output Resistance	R_{SEG} (L)	—	SEG	$V_{OUT} = V_{DD} - 0.5V$	—	—	90	$k\Omega$

PARAMETER	SYMBOL	TEST CIR- CUIT	PIN NAME	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
"1" Output Resistance	R _{SEG} (H)	—	SEG	V _{OUT} = V _{SS} + 0.5V : KEY STROBE	—	—	90	kΩ
"0" Output Resistance	R _{COM} (L)	—	COM	V _{OUT} = V _{DD} - 0.5V	—	—	25	kΩ
"1" Output Resistance	R _{COM} (H)	—	COM	V _{OUT} = V _{SS} + 0.5V	—	—	25	kΩ
KEY PULL UP Resistance	R _{PULL UP}	—	K ₁	V _{OUT} = 0V	27	45	63	kΩ
KEY PULL DOWN Resistance	R _{PULL DOWN}	—	K ₂ ~K ₄	V _{OUT} = V _{SS}	27	45	63	kΩ
"M" Output Resistance	R _{OM}	—	SEG	V _{OUT} = $\frac{1}{3}$ V _{SS} - 0.5V	—	100	—	kΩ
"M" Output Resistance	R _{OM}	—	SEG	V _{OUT} = $\frac{2}{3}$ V _{SS} + 0.5V	—	100	—	kΩ
"M" Output Resistance	R _{OM}	—	COM	V _{OUT} = $\frac{1}{3}$ V _{SS} - 0.5V	—	77	—	kΩ
"M" Output Resistance	R _{OM}	—	COM	V _{OUT} = $\frac{2}{3}$ V _{SS} + 0.5V	—	77	—	kΩ
"1" Output Voltage	V _{OH}	—	K ₁	(Note 1)	V _{SS} + 0.2	V _{SS}	V _{SS}	V
"0" Output Voltage	V _{OL}	—	K ₂ ~K ₄	(Note 1)	V _{DD}	V _{DD}	V _{DD} - 0.2	V
"1" Output Voltage	V _{OH}	—	SEG COM	—	V _{SS} + 0.2	V _{SS}	V _{SS}	V
"M" Output Voltage	V _{OM}	—	SEG COM	—	$\frac{2}{3}$ V _{SS} + 0.2	$\frac{2}{3}$ V _{SS}	$\frac{2}{3}$ V _{SS} - 0.2	V
"M" Output Voltage	V _{OM}	—	SEG COM	—	$\frac{1}{3}$ V _{SS} + 0.2	$\frac{1}{3}$ V _{SS}	$\frac{1}{3}$ V _{SS} - 0.2	V
"0" Output Voltage	V _{OL}	—	SEG COM	—	V _{DD}	V _{DD}	V _{DD} - 0.2	V


(Note 1) The key buffer is high impedance at keystroke.

WAVEFORMS FOR DISPLAY

Display




Key pulse output

(Note 1) $F_{\phi} \text{ WAIT} = 30\text{kHz}$ (Note 2) $F_{\phi} \text{ OP} = 70\text{kHz}$

OUTLINE DRAWING

LQFP60-P-1414-0.80

Unit : mm



Weight : 0.66g (Typ.)